

Application Note

EI2C MasterSlave

Arm and Keil are registered trademarks of Arm Limited (or its subsidiaries) in the US and/or elsewhere.

All other company names, product names, and service names mentioned herein may be trademarks of their respective companies.

Table of Contents

Table of Contents.....	2
1. Preface	3
2. Technical Term	3
3. Reference Document	3
4. Target Sample Program	4
5. Configuration Diagram	4
6. Sample Program : EI2C_MasterSlave	5
6.1. Outlines of Operation	5
6.2. Function to Use.....	6
6.3. Interrupt to Use	6
6.4. Configuration.....	6
6.5. Example of Terminal Emulator Output	7
6.5.1. Normal Operation	7
6.5.2. Case of Error Occurrence	9
7. EI2C Driver	9
8. Revision History	10
RESTRICTIONS ON PRODUCT USE	11

1. Preface

This application note describes sample software for the I2C Master and Slave control functions using the I2C driver.

This document helps the user check operation of a product under development and develop its program.

2. Technical Term

Term/Abbreviation	Definition
I2C	Inter-Integrated Circuit interface version A
BSP	Board Support Package
UART	Universal Asynchronous Receiver Transmitter


3. Reference Document

Document	Notes
Data sheet	Refer to the data sheet of MCU to be used.
Reference manual	Refer to the reference manual of each IP to be used.
Application note MCU User Guide	Refer to the MCU user guide to be used.

4. Target Sample Program

Sample Program	Outline
EI2C_MasterSlave	Sample program of EI2C_MasterSlave function

5. Configuration Diagram



6. Sample Program : I2C_MasterSlave

This is sample software to check the operation of I2C Master and Slave according to the command input from the terminal emulator.

6.1. Outlines of Operation

It is divided into Master operation and Slave operation.

Master: Enter commands (write, read) from the terminal emulator.

Slave: When a Request from Master is received, I2C control is used and the result is output according to the command.

Slave_address is displayed in the terminal emulator as "sa xx".

Command list

Command	function	Parameters (hex)		Input sample	Note
		1	2		
write	Data transmission	XX	XX...	"write" "write 60" "write 6011223344"	<ul style="list-style-type: none"> [dataA_form1]: Send INIT_SLAVE with no parameters [dataA_form2]: Send INIT_WDATA with no parameters The transmission size is the total number of bytes of [dataA_form1] + [dataA_form2]
		[dataA_form1] (Slave_address) (1 byte)	[dataA_form2] (Master_tx_data) (max 4 byte)		
read	Data transmission + Data reception	XX	XX...	"read" "read 60" "read 600001"	<ul style="list-style-type: none"> [dataB_form1]: Same specifications as [dataA_form1] [dataB_form2]: This is the read size when reading from the Sub Address or later of [dataB_form1]. Send INIT_RNUM with no parameters Send / receive size Send: Number of bytes in [dataB_form1] Receive: Number of bytes in [dataB_form2]
		[dataB_form1] (Slave_address) (1 byte)	[dataB_form2] (Master_tx_data) (1 byte, 2 byte)		
slave	Switch to Slave Mode	-	-	"slave"	<ul style="list-style-type: none"> [dataC_form1]: Same specifications as [dataA_form1] After switching, wait for the Slave Address to be received. If you make a request more than the number of times set in SLAVE_CONTINUE, it will return from Slave mode to Master mode
		-	-		

Note 1) "XX" is a hex number. For 0x12, enter "12".

Note 2) The parameter of [] is accepted even if it is not specified.

6.2. Function to Use

The functions to use are as follows.

For the Port assignment of each channel, refer to the MCU user guide.

IP	Channel	Objective
EI2C	BSP_EI2C_1	For EI2C control. Works as a Master Device or Slave Device
UART	BSP_UART_1	For terminal emulator communication. Used for operation log output and command input

6.3. Interrupt to Use

Interrupt	Outlines
INTI2C1NST	EI2C ch.1 Status interrupt
INTI2C1ATX	EI2C ch.1 Send buffer empty interrupt
INTI2C1BRX	EI2C ch.1 Receive buffer empty interrupt
INTUART0RX	UART ch0 Receive interrupt. For terminal emulator
INTUART0TX	UART ch0 Transmission interrupt. For terminal emulator
INTUART0ERR	UART ch0 Error interrupt. For terminal emulator

6.4. Configuration

“main.c” configuration setting.

Configuration	Current Value	Description
INIT_SLAVE	Slave Address	-
INIT_WDATA	11, 22, 33, 44	4 bytes are used as write data
INIT_RNUM	0x02	Number of read request bytes of 2 bytes
Sub address	Start sub Address	-
PARAM A Size Max	0x04	Number of received bytes of [dataA_form2]
PARAM B Size Max	0x02	Number of received bytes of [dataB_form2]
SLAVE_CONTINUE	10	When Slave is operating, if you make a request that exceeds the number of times set in SLAVE_CONTINUE, it will return from Slave mode to Master mode

6.5. Example of Terminal Emulator Output

6.5.1. Normal Operation

Write Command

Master

Slave (slave address 60)

When [dataA_form1] and [dataA_form2] are saved

```
command > write
master
sa 60
tx[0] 11
tx[1] 22
tx[2] 33
tx[3] 44
```

write command →
INIT_SLAVE
=0x60 (case)

INIT_WDATA
=11,22,33,44 (case)

```
rx[0] 11
rx[1] 22
rx[2] 33
rx[3] 44
slave
sa 60
```

When [dataA_form2] is saved

```
command > write 60
master
sa 60
tx[0] 11
tx[1] 22
tx[2] 33
tx[3] 44
```

write command →

INIT_WDATA
=11,22,33,44 (case)

```
rx[0] 11
rx[1] 22
rx[2] 33
rx[3] 44
slave
sa 60
```

When [dataA_form1] and [dataA_form2] are not labor-saving

```
command > write 6055667788
master
sa 60
tx[0] 55
tx[1] 66
tx[2] 77
tx[3] 88
```

write command →

```
rx[0] 55
rx[1] 66
rx[2] 77
rx[3] 88
slave
sa 60
```

Read Command

Master

Slave (slave address 60)

When [dataB_form1] and [dataB_form2] are saved

```
command > read  
master  
sa 60  
rx[0] 11  
rx[1] 22
```

read command →

INIT_SLAVE
=0x60 (case)

INIT_RNUM
=0x0002 (case)

```
tx[0] 11  
tx[1] 22  
slave  
sa 60
```

When [dataB_form2] is saved

```
command > read 60  
master  
sa 60  
rx[0] 11  
rx[1] 22
```

read command →

INIT_RNUM
=0x0002 (case)

```
tx[0] 11  
tx[1] 22  
slave  
sa 60
```

When [dataB_form1] and [dataB_form2] are not labor-saving

```
command > read 600001  
master  
sa 60  
rx[0] 11
```

read command →

```
tx[0] 11  
slave  
sa 60
```


Slave Command

Master

```

-----
| I2C master mode |
-----
command >
    
```

slave command →

Slave

```

-----
| I2C master mode |
-----
command > slave
-----
| I2C slave mode |
-----
slave
sa 60
    
```

6.5.2. Case of Error Occurrence

Nothing.

7. I2C Driver

The I2C is controlled by using the following interface.
For an example of use, refer to the source code.

Driver	Control Outlines
EI2C_init	EI2C Register initialization
EI2C_restartcondition	Generate restart condition
EI2C_startcondition	Generate start condition
EI2C_slave_init	Slave mode setting

8. Revision History

Revision	Date	Description
1.0	2023-06-28	First release

RESTRICTIONS ON PRODUCT USE

Toshiba Corporation and its subsidiaries and affiliates are collectively referred to as "TOSHIBA". Hardware, software and systems described in this document are collectively referred to as "Product".

- TOSHIBA reserves the right to make changes to the information in this document and related Product without notice.
- This document and any information herein may not be reproduced without prior written permission from TOSHIBA. Even with TOSHIBA's written permission, reproduction is permissible only if reproduction is without alteration/omission.
- Though TOSHIBA works continually to improve Product's quality and reliability, Product can malfunction or fail. Customers are responsible for complying with safety standards and for providing adequate designs and safeguards for their hardware, software and systems which minimize risk and avoid situations in which a malfunction or failure of Product could cause loss of human life, bodily injury or damage to property, including data loss or corruption. Before customers use the Product, create designs including the Product, or incorporate the Product into their own applications, customers must also refer to and comply with (a) the latest versions of all relevant TOSHIBA information, including without limitation, this document, the specifications, the data sheets and application notes for Product and the precautions and conditions set forth in the "TOSHIBA Semiconductor Reliability Handbook" and (b) the instructions for the application with which the Product will be used with or for. Customers are solely responsible for all aspects of their own product design or applications, including but not limited to (a) determining the appropriateness of the use of this Product in such design or applications; (b) evaluating and determining the applicability of any information contained in this document, or in charts, diagrams, programs, algorithms, sample application circuits, or any other referenced documents; and (c) validating all operating parameters for such designs and applications. **TOSHIBA ASSUMES NO LIABILITY FOR CUSTOMERS' PRODUCT DESIGN OR APPLICATIONS.**
- **PRODUCT IS NEITHER INTENDED NOR WARRANTED FOR USE IN EQUIPMENTS OR SYSTEMS THAT REQUIRE EXTRAORDINARILY HIGH LEVELS OF QUALITY AND/OR RELIABILITY, AND/OR A MALFUNCTION OR FAILURE OF WHICH MAY CAUSE LOSS OF HUMAN LIFE, BODILY INJURY, SERIOUS PROPERTY DAMAGE AND/OR SERIOUS PUBLIC IMPACT ("UNINTENDED USE").** Except for specific applications as expressly stated in this document, Unintended Use includes, without limitation, equipment used in nuclear facilities, equipment used in the aerospace industry, lifesaving and/or life supporting medical equipment, equipment used for automobiles, trains, ships and other transportation, traffic signaling equipment, equipment used to control combustions or explosions, safety devices, elevators and escalators, and devices related to power plant. **IF YOU USE PRODUCT FOR UNINTENDED USE, TOSHIBA ASSUMES NO LIABILITY FOR PRODUCT.** For details, please contact your TOSHIBA sales representative or contact us via our website.
- Do not disassemble, analyze, reverse-engineer, alter, modify, translate or copy Product, whether in whole or in part.
- Product shall not be used for or incorporated into any products or systems whose manufacture, use, or sale is prohibited under any applicable laws or regulations.
- The information contained herein is presented only as guidance for Product use. No responsibility is assumed by TOSHIBA for any infringement of patents or any other intellectual property rights of third parties that may result from the use of Product. No license to any intellectual property right is granted by this document, whether express or implied, by estoppel or otherwise.
- **ABSENT A WRITTEN SIGNED AGREEMENT, EXCEPT AS PROVIDED IN THE RELEVANT TERMS AND CONDITIONS OF SALE FOR PRODUCT, AND TO THE MAXIMUM EXTENT ALLOWABLE BY LAW, TOSHIBA (1) ASSUMES NO LIABILITY WHATSOEVER, INCLUDING WITHOUT LIMITATION, INDIRECT, CONSEQUENTIAL, SPECIAL, OR INCIDENTAL DAMAGES OR LOSS, INCLUDING WITHOUT LIMITATION, LOSS OF PROFITS, LOSS OF OPPORTUNITIES, BUSINESS INTERRUPTION AND LOSS OF DATA, AND (2) DISCLAIMS ANY AND ALL EXPRESS OR IMPLIED WARRANTIES AND CONDITIONS RELATED TO SALE, USE OF PRODUCT, OR INFORMATION, INCLUDING WARRANTIES OR CONDITIONS OF MERCHANTABILITY, FITNESS FOR A PARTICULAR PURPOSE, ACCURACY OF INFORMATION, OR NONINFRINGEMENT.**
- Do not use or otherwise make available Product or related software or technology for any military purposes, including without limitation, for the design, development, use, stockpiling or manufacturing of nuclear, chemical, or biological weapons or missile technology products (mass destruction weapons). Product and related software and technology may be controlled under the applicable export laws and regulations including, without limitation, the Japanese Foreign Exchange and Foreign Trade Law and the U.S. Export Administration Regulations. Export and re-export of Product or related software or technology are strictly prohibited except in compliance with all applicable export laws and regulations.
- Please contact your TOSHIBA sales representative for details as to environmental matters such as the RoHS compatibility of Product. Please use Product in compliance with all applicable laws and regulations that regulate the inclusion or use of controlled substances, including without limitation, the EU RoHS Directive. **TOSHIBA ASSUMES NO LIABILITY FOR DAMAGES OR LOSSES OCCURRING AS A RESULT OF NONCOMPLIANCE WITH APPLICABLE LAWS AND REGULATIONS.**

Toshiba Electronic Devices & Storage Corporation

<https://toshiba.semicon-storage.com/>